

### Overview

## Aruba 370 Series Access Points

High performance 802.11ac Wave 2 for outdoor environments

### Product overview

Weatherproof and temperature hardened, Aruba 370 series access points deliver 802.11ac Wave 2 Gigabit Wi-Fi to outdoor and environmentally challenging locations. The 370 high-performance and high power series deliver maximum capacity and range. It delivers 4x4:4SS MU-MIMO capability, Aruba's advanced ClientMatch and an integrated Bluetooth beacon to enable Aruba location services.

Purpose-built to survive in the harshest outdoor environments, 370 Series APs can withstand exposure to extreme high and low temperatures, persistent moisture and precipitation, and are fully sealed to keep out airborne contaminants. All electrical interfaces include industrial strength surge protection.

With a maximum concurrent data rate of 1,733 Mbps in the 5 GHz band and 300 Mbps in the 2.4 GHz band (for an aggregate peak data rate of 2.0 GBPS), the Aruba 370 Series Access Points can quickly add required capacities to your existing or new wireless networks.

The high performance and high density 802.11ac the 370 Series supports 160 MHz channel bandwidth (VHT160), multi-user MIMO (MU-MIMO) and 4 spatial streams (4SS).

Proactive and deterministic, ClientMatch dynamically optimizes Wi-Fi client performance as users roam and RF conditions change. If a mobile device moves away from an AP or RF interference impedes performance, ClientMatch automatically steers it to a better AP.

With ClientMatch, clients load web pages faster, deliver video streams with improved quality and support high densities of mobile devices. An 802.11ac network without ClientMatch performs no different than an 802.11n WLAN.

The 370 Series also has an integrated Bluetooth Aruba Beacon that simplifies the remote management of a network of large-scale battery-powered Aruba beacons while also providing advanced location and way finding, and proximitybased push notification capabilities. It enables businesses to leverage mobility context to develop applications that can deliver an enhanced user experience and increases the value of the wireless network for organizations.

---

## Features and Benefits

### Unique Benefits

- Dual Radio 802.11ac access point with Multi-User MIMO
  - Supports up to 1,733 Mbps in the 5 GHz band (with 4SS/VHT80 or 2SS/VHT160 clients) and up to 300 Mbps in the 2.4 GHz band (with 2SS/HT40 clients).
- Built-in Bluetooth Low-Energy (BLE) radio
  - Enables location-based services with BLE-enabled mobile devices receiving signals from multiple Aruba Beacons at the same time.
- Advanced Cellular Coexistence (ACC)
  - Minimizes interference from 3G/4G cellular networks, distributed antenna systems, and commercial small cell/femtocell equipment.
- Industrial design for harsh indoor and outdoor environments
  - Sealed connector interfaces to lock out dust and moisture
- Quality of service for unified communication apps

### Overview

- Supports priority handling and policy enforcement for unified communication apps, including Microsoft Skype for Business with encrypted videoconferencing, voice, chat, and desktop sharing.
- Best-in-class RF management
  - Integrated AirMatch technology manages the 2.4-GHz and 5-GHz radio bands and actively optimizes the RF environment including channel width, channel selection and transmit power.
- Spectrum analysis
  - Capable of part-time or dedicated air monitoring, the spectrum analyzer remotely scans the 2.4-GHz and 5-GHz radio bands to identify sources of RF interference.
- Wireless mesh
  - Wireless mesh connections are convenient where Ethernet drops are not available.
- Intelligent app visibility and control
  - AppRF technology leverages deep packet inspection to classify and block, prioritize, or limit bandwidth for thousands of applications in a range of categories.
- Aruba Secure Core
  - Device assurance: Use of Trusted Platform Module (TPM) for secure storage of credentials and keys as well as secure boot
  - Integrated wireless intrusion protection offers threat protection and mitigation and eliminates the need for separate RF sensors and security appliances.
  - IP reputation and security services identify, classify, and block malicious files, URL and IPs, providing comprehensive protection against advanced online threats.
  - Encrypted IPsec VPN tunnels securely connect remote users to corporate network resources.

### Choose your operating mode

As unified APs, the Aruba 370 Series can be deployed with or without a controller and can be readily switched to accommodate changing network needs.

- Controller mode: When managed by Aruba Mobility Controllers, Aruba 370 Series APs offer centralized configuration, data encryption, policy enforcement and network services, as well as distributed and centralized traffic forwarding or,
- Controllerless (Instant) mode: In Aruba Instant mode, a single AP automatically distributes the network configuration to other Instant APs in the WLAN. Simply power-up one Instant AP, configure it over the air, and plug in the other APs - Instant Network.

Other functional modes include:

- Remote AP (RAP) mode for branch deployments
- Air monitor (AM) for wireless IDS, rogue detection and containment
- Spectrum analyzer, dedicated or hybrid, for identifying sources of RF interference
- Secure enterprise mesh
- Hybrid AP serves Wi-Fi clients and provides wireless intrusion protection and spectrum analysis

For large installations across multiple sites, the Aruba Activate service significantly reduces deployment time by automating device provisioning, firmware upgrades, and inventory management. With Aruba Activate, Unified APs are factory-shipped to any site and configure themselves when powered up.

### Aruba 370 Series Specifications

- AP-374

### Overview

- 5 GHz 802.11ac 4x4 MU-MIMO (1,733 Mbps max rate)
  - ✍ Four Nf connectors for external antenna operation
- 2.4 GHz 802.11n 2x2 MIMO (300 Mbps max rate) radios
  - ✍ Two Nf connectors for external antenna operation at 2.4 GHz.

- AP-375

- 5 GHz 802.11ac 4x4 MU-MIMO (1,733 Mbps max rate)
  - ✍ Internal Omni Antennas 4.6 dBi
- 2.4 GHz 802.11n 2x2 MIMO (300 Mbps max rate) radios
  - ✍ Internal Omni Antennas 4.0 dBi

- AP-377

- 5 GHz 802.11ac 4x4 MU-MIMO (1,733 Mbps max rate)
  - ✍ Internal 80°H x 80°V Directional Antennas 6.3 dBi
- 2.4 GHz 802.11n 2x2 MIMO (300 Mbps max rate) radios
  - ✍ Internal 80°H x 80°V Directional Antennas 6.4 dBi

### WI-FI Radio Specifications

- AP type: Outdoor hardened, dual radio, 5 GHz 802.11ac 4x4 MIMO and 2.4 GHz 802.11n 2x2 MIMO
- Software-configurable dual radio supports 5 GHz (Radio 0) and 2.4 GHz (Radio 1)
- 5 GHz: Four spatial stream Multi User (MU) MIMO for up to 1,733 Mbps wireless data rate to up to three MU-MIMO capable client devices simultaneously
- 5 GHz: Four spatial stream Single User (SU) MIMO for up to 1,733 Mbps wireless data rate to individual 4x4 VHT80 or 2x2 VHT160 client devices
- 2.4 GHz: Two spatial stream Single User (SU) MIMO for up to 300 Mbps wireless data rate to individual 2x2 HT40 client devices
- Support for up to 256 associated client devices per radio, and up to 16 BSSIDs per radio
- Supported frequency bands (country-specific restrictions apply):

- 2.400 to 2.4835 GHz

- 5.150 to 5.250 GHz

- 5.250 to 5.350 GHz

- 5.470 to 5.725 GHz

- 5.725 to 5.850 GHz

- Available channels: Dependent on configured regulatory domain.
- Dynamic frequency selection (DFS) maximizes the use of available RF spectrum.
- Supported radio technologies:
  - 802.11b: Direct-sequence spread-spectrum (DSSS)
  - 802.11a/g/n/ac: Orthogonal frequency-division multiplexing (OFDM)

- Supported modulation types:

### Overview

- 802.11b: BPSK, QPSK, CCK
- 802.11a/g/n/ac: BPSK, QPSK, 16-QAM, 64-QAM, 256-QAM
- Transmit power: Configurable in increments of 0.5 dBm
- Maximum (conducted) transmit power (limited by local regulatory requirements):
  - 2.4 GHz band: +22 dBm per chain, +25dBm aggregate (2x2)
  - 5 GHz band: +22 dBm per chain, +28dBm aggregate (4x4)
  - **NOTE:** conducted transmit power levels exclude antenna gain.
- Maximum EIRP (limited by local regulatory requirements):
  - 2.4 GHz band:
    - ⊙ 374: 25 + Antenna Gain
    - ⊙ 375: 29 dBm EIRP
    - ⊙ 377: 31.4 dBm EIRP
  - 5 GHz band:
    - ⊙ 374: 28 + Antenna Gain + TxBF Gain
    - ⊙ 375: 35.6 dBm EIRP
    - ⊙ 377: 36 dBm EIRP
- Advanced Cellular Coexistence (ACC) minimizes interference from cellular networks.
- Maximum ratio combining (MRC) for improved receiver performance.
- Cyclic delay/shift diversity (CDD/CSD) for improved downlink RF performance.
- Short guard interval for 20-MHz, 40-MHz, 80-MHz and 160-MHz channels.
- Space-time block coding (STBC) for increased range and improved reception.
- Low-density parity check (LDPC) for high-efficiency error correction and increased throughput.
- Transmit beam-forming (TxBF) for increased signal reliability and range.
- Supported data rates (Mbps):
  - 802.11b: 1, 2, 5.5, 11
  - 802.11a/g: 6, 9, 12, 18, 24, 36, 48, 54
  - 802.11n (2.4GHz): 6.5 to 300 (MCS0 to MCS15)
  - 802.11n (5GHz): 6.5 to 600 (MCS0 to MCS31)
  - 802.11ac: 6.5 to 1,733 (MCS0 to MCS9, NSS = 1 to 4 for VHT20/40/80, NSS = 1 to 2 for VHT160)
- 802.11n high-throughput (HT) support: HT 20/40
- 802.11ac very high throughput (VHT) support: VHT 20/40/80/160
- 802.11n/ac packet aggregation: A-MPDU, A-MSDU

### Power

- Worst-case power consumption from the AP: 23W
- Power sources sold separately
- Power over Ethernet (PoE+): 802.3at-compliant
- AC Power: 100-240 Volt 50/60Hz AC

### Other Interfaces

### Overview

- One 10/100/1000BASE-T Ethernet network interfaces (RJ-45)
  - Auto-sensing link speed and MDI/MDX
  - 802.3az Energy Efficient Ethernet (EEE)
- One 1000BASE-X SFP Port
- Bluetooth Low Energy (BLE) radio
  - Up to 4 dBm transmit power (class 2) and -91 dBm receive sensitivity
- Visual indicator (multi-color LED): For system and radio status
- Reset button: Factory reset (during device power up)
- Micro USB console interface
- Kensington security slot

### Mounting

- AP-270-MNT-V1
- AP-270-MNT-V2
- AP-270-MNT-H1
- AP-270-MNT-H2

### Mechanical

#### AP-374

Dimensions/weight (excluding mount):

- 23 cm (W) x 24 cm (D) x 19 cm (H) with aesthetic cover
- 9.0" (W) x 9.4" (D) x 7.5" (H)
- 2.7 kg/6 lbs
- 23 cm (W) x 24 cm (D) x 14 cm (H) without aesthetic cover
- 9.0" (W) x 9.4" (D) x 5.5" (H)
- 2.4 kg/5.3 lbs

#### AP-375

Dimensions/weight (excluding mount):

- 23 cm (W) x 24 cm (D) x 27 cm (H)
- 9.0" (W) x 9.4" (D) x 10.6" (H)
- 2.4 kg/5.3 lbs

#### AP-377

Dimensions/weight (excluding mount):

- 23 cm (W) x 22 cm (D) x 13 cm (H)
- 9.0" (W) x 8.7" (D) x 5.1" (H)
- 2.1 kg/4.6 lbs

### Environmental

- Operating:
  - Temperature: -40° C to +65° C (-40° F to +149° F)
  - Humidity: 5% to 95% non-condensing
- Storage and transportation:
  - Temperature: -40° C to +70° C (-40° F to +158° F)
- Operating Altitude: 3,000 m
- Water and Dust

### Overview

- IP66/67

- Salt Tolerance

- Tested to ASTM B117-07A Salt Spray 200hrs

- Wind Survival: Up to 165 Mph
- Shock and Vibration ETSI 300-19-2-4

### Regulatory

- FCC/ISED
- CE Marked
- RED Directive 2014/53/EU
- EMC Directive 2014/30/EU
- Low Voltage Directive 2014/35/EU
- UL/IEC/EN 60950
- EN 60601-1-1, EN60601-1-2

For more country-specific regulatory information and approvals, please see your Aruba representative.

### Regulatory Model Numbers

- AP-374: APEX0374
- AP-375: APEX0375
- AP-377: APEX0377

### Certifications

- CB Scheme Safety, cTUVus
- UL2043 plenum rating
- Wi-Fi Alliance certified 802.11a/b/g/n
- Wi-Fi CERTIFIED™ ac (with wave 2 features)

### Warranty

- Limited lifetime warranty

### Minimum Operating System Software

- ArubaOS & Aruba InstantOS 8.3.0.0
-

### Configuration

## Ordering Information

### Step 1: Select AP Model

Description	Part Number
<b>Unified Outdoor Access Points</b>	
Aruba AP-374 (RW) 802.11n/ac Dual 2x2:2/4x4:4 Radio 6xNf Connectors Outdoor AP	JZ162A
Aruba AP-374 (US) 802.11n/ac Dual 2x2:2/4x4:4 Radio 6xNf Connectors Outdoor AP	JZ163A
Aruba AP-374 (EG) 802.11n/ac Dual 2x2:2/4x4:4 Radio 6xNf Connectors Outdoor AP	JZ159A
Aruba AP-374 (IL) 802.11n/ac Dual 2x2:2/4x4:4 Radio 6xNf Connectors Outdoor AP	JZ160A
Aruba AP-374 (JP) 802.11n/ac Dual 2x2:2/4x4:4 Radio 6xNf Connectors Outdoor AP	JZ161A
Aruba AP-375 (RW) 802.11n/ac Dual 2x2:2/4x4:4 Radio Integrated Omni Antenna Outdoor AP	JZ172A
Aruba AP-375 (US) 802.11n/ac Dual 2x2:2/4x4:4 Radio Integrated Omni Antenna Outdoor AP	JZ173A
Aruba AP-375 (EG) 802.11n/ac Dual 2x2:2/4x4:4 Radio Integrated Omni Antenna Outdoor AP	JZ169A
Aruba AP-375 (IL) 802.11n/ac Dual 2x2:2/4x4:4 Radio Integrated Omni Antenna Outdoor AP	JZ170A
Aruba AP-375 (JP) 802.11n/ac Dual 2x2:2/4x4:4 Radio Integrated Omni Antenna Outdoor AP	JZ171A
Aruba AP-377 (RW) 802.11n/ac Dual 2x2:2/4x4:4 Radio Integrated Directional Antenna Outdoor	JZ182A
Aruba AP-377 (US) 802.11n/ac Dual 2x2:2/4x4:4 Radio Integrated Directional Antenna Outdoor	JZ183A
Aruba AP-377 (EG) 802.11n/ac Dual 2x2:2/4x4:4 Radio Integrated Directional Antenna Outdoor	JZ179A
Aruba AP-377 (IL) 802.11n/ac Dual 2x2:2/4x4:4 Radio Integrated Directional Antenna Outdoor	JZ180A
Aruba AP-377 (JP) 802.11n/ac Dual 2x2:2/4x4:4 Radio Integrated Directional Antenna Outdoor	JZ181A
<b>Unified Outdoor Access Points FIPS/TAA</b>	
Aruba AP-374 (RW) FIPS/TAA 802.11n/ac Dual 2x2:2/4x4:4 Radio 6xNf Connectors Outdoor AP	JZ167A
Aruba AP-374 (US) FIPS/TAA 802.11n/ac Dual 2x2:2/4x4:4 Radio 6xNf Connectors Outdoor AP	JZ168A
Aruba AP-374 (EG) FIPS/TAA 802.11n/ac Dual 2x2:2/4x4:4 Radio 6xNf Connectors Outdoor AP	JZ164A
Aruba AP-374 (IL) FIPS/TAA 802.11n/ac Dual 2x2:2/4x4:4 Radio 6xNf Connectors Outdoor AP	JZ165A
Aruba AP-374 (JP) FIPS/TAA 802.11n/ac Dual 2x2:2/4x4:4 Radio 6xNf Connectors Outdoor AP	JZ166A
Aruba AP-375 (RW) FIPS/TAA 802.11n/ac Dual 2x2:2/4x4:4 Radio Integrated Omni Antenna Outdoor AP	JZ177A
Aruba AP-375 (US) FIPS/TAA 802.11n/ac Dual 2x2:2/4x4:4 Radio Integrated Omni Antenna Outdoor AP	JZ178A
Aruba AP-375 (EG) FIPS/TAA 802.11n/ac Dual 2x2:2/4x4:4 Radio Integrated Omni Antenna Outdoor AP	JZ174A
Aruba AP-375 (IL) FIPS/TAA 802.11n/ac Dual 2x2:2/4x4:4 Radio Integrated Omni Antenna Outdoor AP	JZ175A

### Configuration

Aruba AP-375 (JP) FIPS/TAA 802.11n/ac Dual 2x2:2/4x4:4 Radio Integrated Omni Antenna Outdoor AP	JZ176A
Aruba AP-377 (RW) FIPS/TAA 802.11n/ac Dual 2x2:2/4x4:4 Radio Integ Directional Antenna Outdoor AP	JZ187A
Aruba AP-377 (US) FIPS/TAA 802.11n/ac Dual 2x2:2/4x4:4 Radio Integ Directional Antenna Outdoor AP	JZ188A
Aruba AP-377 (EG) FIPS/TAA 802.11n/ac Dual 2x2:2/4x4:4 Radio Integ Directional Antenna Outdoor AP	JZ184A
Aruba AP-377 (IL) FIPS/TAA 802.11n/ac Dual 2x2:2/4x4:4 Radio Integ Directional Antenna Outdoor AP	JZ185A
Aruba AP-377 (JP) FIPS/TAA 802.11n/ac Dual 2x2:2/4x4:4 Radio Integ Directional Antenna Outdoor AP	JZ186A

### Step 2: Add mounting bracket

Description	Part Number
AP-270-MNT-V1 AP-270 Series Outdoor Pole/Wall Long Mount Kit	JW052A
AP-270-MNT-V2 AP-270 Series Outdoor Pole/Wall Short Mount Kit	JW053A
AP-270-MNT-H1 AP-270 Series Outdoor AP Hanging or Tilt Install Mount Kit	JW054A
AP-270-MNT-H2 AP-270 Series Access Flush Wall or Ceiling Mount	JW055A

**NOTE:** The AP-270-MNT-V2 bracket cannot be used if the unit is operated with an SFP module

**NOTE:** The V1 and V2 brackets are most commonly used with Aruba 374 and 375. The H1 and H2 brackets are most commonly used to wall mount an Aruba 377 or to hang the Aruba 374/375 from a horizontal surface.

### Step 3: Add outdoor power cable for unites to be powered from AC (110/220V)

Description	Part Number
PC-OD-AC-P-NA MST2HAC and AP-27x Weatherized AC Power 5m North Amer Cable	JW081A
PC-OD-AC-P-INT MST2HAC and AP-27x Weatherized AC Power 5m International Cable	JW080A
CKIT-OD-AC-P MST2HAC and AP-27x Custom AC Power Cable Connector Assembly Kit	JW079A

### Step 4: Add SPF for fiber connection (optional)

Description	Part Number
SFP-LX Extended Temperature 1000BASE-LX SFP 1310nm LC Connector Pluggable GbE XCVR	Q8N52A
SFP-SX Extended Temperature 1000BASE-SX SFP 850nm LC Connector Pluggable GbE XCVR	Q8N53A
Outdoor SFP Weathertight Strain Relief Kit	Q8N54A

**NOTE:** Q8N54A is a mandatory items if an SFP is used.

### Step 5: Add POE powering accessories for units to be POE powered

Description	Part Number
PD-9001GO-NA 30W 802.3at PoE+ 10/100/1000 Outdoor Surge Prot NA Power Cord Mdsan Injector	JW700A
PD-9001GO-INTL 30W 802.3at PoE+ 10/100/1000 Outdoor Surge Prot Intl Power Cord Injector	JW701A

### Configuration

PD-9001GO-DC 30W 802.3at PoE+ 10/100/1000 12-24V DC in Outdoor Surge Prot Midspan Injector	JW630A
PD-9001GR-AC 30W 802.3at PoE+ 10/100/1000 Ethernet Indoor Rated Midspan Injector	JW629A

### Step 6: Add mounting kit for outdoor POE Midspan injector (optional)

Description	Part Number
PD-MOUNT-OD Outdoor PoE Midspan Injectors Pole/Mast Mount Kit	JW620A

### Step 7: Select 3-Prong AC power cord for indoor POE injector

Description	Part Number
PC-AC-ARG Argentina 220V AC 10A 2-meter AC Power Cord	JW113A
PC-AC-AUS Australian AC Power Cord	JW114A
PC-AC-BR Brazil AC Power Cord	JW115A
PC-AC-CHN China AC Power Cord	JW116A
PC-AC-DEN Denmark 220V AC 10A 2-meter AC Power Cord	JW117A
PC-AC-EC Continental European/Schuko AC Power Cord	JW118A
PC-AC-IN India AC Power Cord	JW119A
PC-AC-IL Israel 250V AC 10A 2-meter AC Power Cord	JW120A
PC-AC-IT Italian AC Power Cord	JW121A
PC-AC-JP Japanese AC Power Cord	JW122A
PC-AC-KOR Korea AC Power Cord	JW123A
PC-AC-NA North America AC Power Cord	JW124A
PC-AC-SWI Switzerland 220V AC 10A 2-meter AC Power Cord	JW125A
PC-AC-TW Taiwan AC Power Cord	JW126A
PC-AC-UK UK AC Power Cord	JW127A
PC-AC-ZA South Africa 250V AC 10A 2-meter AC Power Cord	JW128A

### Step 8: Add antenna for radio 0 (5 GHZ) (Aruba 374 only)

Description	Part Number
ANT-2x2-5005 Pair 5GHz 5dBi Omni N-type Direct Mount Outdoor Antennas	JW026A
ANT-2x2-5010 Pair 5GHz 10dBi Omni N-Type Direct Mount Outdoor Antennas	JW027A
ANT-4x4-5314 5.15-5.9GHz 14dBi 30x30deg Dual Pol MIMO Hi Gain Dir N-Type Outdoor Antenna	JX988A
ANT-3x3-5712 4.9-5.9GHz 12.0dBi 75x25deg +/- 45deg and V Pol 3 MIMO High-gain Dir Antenna	JW033A
ANT-4x4-D100 Dual-band 90x90deg 5dBi +/- 45 and Vert Pol MIMO N-Type Bracket + Antenna	Q8N50A
ANT-4x4-D608 Dual-band 60x60deg 8dBi +/- 45 and Vert Pol MIMO N-Type Bracket + Antenna	Q8N51A

**NOTE:** 5 GHz radio has 4 connectors so 2 sets of JW026A or JW027A are necessary for full configuration

### Step 9: Add antenna for radio 1 (2.4 GHZ) (Aruba 374 only)

Description	Part Number
ANT-2x2-2005 Pair 2.4GHz 5dBi Omni N-type Direct Mount Outdoor Antennas	JW023A
ANT-2x2-2314 2.4 GHz 14dBi 30x30deg Dual Pol MIMO High Gain Dir N-Type Outdoor Antenna	JW024A
ANT-2x2-2714 2.4G 14dBi 70deg Sector Dual Pol MIMO N-type Outdoor Antenna	JW025A

### Configuration

ANT-3x3-D100 Dual Band 90x90deg 5dBi +/- 45 and Vert Pol MIMO N-Type Antenna	JW034A
ANT-3x3-D608 Dual Band 60x60deg 8dBi +/- 45 and Vert Pol MIMO N-Type Antenna	JW035A

### Step 10: Add RF cables (Aruba 374 only)

Description	Part Number
AP-CBL-1 10ft(3m) Nm to Nf Outdoor Rated RF Cable	JW070A
ANT-CBL-1 1m Nm to Nm Flexible Outdoor Rated RF Cable	JW068A
ANT-CBL-2 2m Nm to Nm Flexible Outdoor Rated RF Cable	JW069A
AFC7DL03-00 3m Nm to Nm Outdoor Rated RF Cable	JW064A
AFC7DL04-00 4m Nm to Nm Outdoor Rated RF Cable	JW065A

### Step 11: Add lightning surge arrestor (Aruba 374 only)

Description	Part Number
AP-LAR-1 Nm to Nf Outdoor DC to 6 GHz In-line Coaxial Lightning Arrestor	JW061A

**NOTE:** Not required unless RF cables are longer than 2m in length

### Step 12: Add installation material (optional Aruba 374 only)

Description	Part Number
AINS2KKIT-00 2 Elec Tape Rolls Mastic Tape and White Tie Wraps Outdoor Install Materials	JW063A

### Step 13: Spares of items that are shipped with the Aruba 370 chassis (optional)

Description	Part Number
Outdoor AP Covers and Glands 1-pk M25/5-pk M20 Cover/2-pk M16 Cover/5-pk M20 Gland/2-pk Ground Kit	Q8N47A
Outdoor AP Metric to Standard M20 to 1/2 inch NPT 5-pk Thread Adapter	Q8N48A

---

### Technical Specifications

#### RF Performance Table

	Maximum transmit power (dBm) per transmit chain	Receiver sensitivity (dBm) per receive chain
<b>802.11b 2.4 GHz</b>		
1 Mbps	22	-95
2 Mbps	22	-93
5.5 Mbps	22	-90
11 Mbps	22	-88
<b>802.11g 2.4 GHz and 802.11a 5 GHz 2.4 GHz and 802.11a 5 GHz</b>		
6 Mbps	22	-93
54 Mbps	19	-75
<b>802.11n HT20 2.4 GHz and 5 GHz</b>		
MCS0/8	22	-93
MCS7/15	18	-71
<b>802.11n HT40 2.4 GHz and 5 GHz</b>		
MCS0/8	22	-90
MCS7/15	18	-68
<b>802.11ac VHT20 5 GHz</b>		
MCS0	22	-93
MCS9	16	-68
<b>802.11ac VHT40 5 GHz</b>		
MCS0	22	-90
MCS9	15	-63
<b>802.11ac VHT80 5 GHz</b>		
MCS0	22	-87
MCS9	15	-61
<b>802.11ac VHT160 5 GHz</b>		
MCS0	22	-86
MCS9	15	-57

## Technical Specifications

**NOTE:** Maximum capability of the hardware provided (excluding antenna gain). Maximum transmit power is limited by local regulatory settings.

### Summary of Changes

Date	Version History	Action	Description of Change
18-Dec-2017	From Version 2 to 3	Changed	Minor changes made on Features and Benefits
04-Dec-2017	From Version 1 to 2	Changed	Updates made on Environmental and Aruba 370 Series Specifications
06-Nov-2017	Version 1	Created	Document creation.



Sign up for updates

---

© Copyright 2017 Hewlett Packard Enterprise Development LP. The information contained herein is subject to change without notice. The only warranties for Hewlett Packard Enterprise products and services are set forth in the express warranty statements accompanying such products and services. Nothing herein should be construed as constituting an additional warranty. Hewlett Packard Enterprise shall not be liable for technical or editorial errors or omissions contained herein.

To learn more, visit: <http://www.hpe.com/networking>

a00027234enw - 16091 - Worldwide - V3 - 18- December-2017

