

90W / 120W



Introduction

NB Slim universal notebook adapter ranges 90W and 120W. NB Slim series featured with close to half thinner thickness compared with traditional adapter, although size is smaller than regular, efficiency keeps over 87%, and conform to DOE VI standards.

Besides, NB Slim includes 9 exchangeable tips, it's compatible with ACER, ASUS, HP, LENOVO...branded notebooks.

FSP NB Slim series also engineering multiple circuit protections of OCP, OVP, SCP and OTP, and get global safety certificated to keep you and your notebook in safe.

Features

- · AC Input:100-240V (Worldwide usage)
- Compatible with 18~20V input laptops
- · High efficiency > 87%, power standby <0.1W
- · Thickness of 25.4mm is half thinner than regular adapter.
- · Compatible with most popular brands of notebooks
- · Complete circuit protections: Over Circuit Protection(OCP), Over Voltage Protection(OVP), Short Circuit Protection(SCP), Over Temperature Protection(OTP)
- · Meets DOE VI, CEC efficiency standards
- Multiple safety approval



90W / 120W

Product Overview

High Efficiency, Energy-saving

NB Slim efficiency meets DOE VI Standards, over 87% efficiency in operation and less 0.1 W in standby mode.



Efficiency Level: VI

Why should we choose high efficiency power supply adapter?

The EPA estimates that external power supply efficiency regulations implemented over the past decade have reduced energy consumption by 32 billion kilowatts, saving \$2.5 billion annually and reducing CO2 emissions by more than 24 million tons per year, let's continue to implement green power supply and make our environment greener.






Product Overview

Thickness is close to half thinner, lighter and save more space.







360° Safety Circuit Protection

NB Slim series is engineering multiple circuit protections of Over Circuit Protection(OCP), Over Voltage Protection(OVP), Short Circuit Protection(SCP), Over Temperature Protection(OTP) and get global safety certificated.






90W / 120W

Product Overview

High Compatibility

NB Slim includes 9 exchangeable tips to support most branded notebooks.




NB Slim Compatibility List

				П				Д	ţ
Tips Number	1	2	3	4	5	8	9	10	U8
Outer(mm)	4.75	5.5	5.5	5.5	6.3	7.9	7.4	5.5	11
Inner(mm)	1.7	1.7	2.1	2.5	3.0	0.9	0.6	1.0	4.65
Color	Yellow	Orange	Blue	White	Green	Black	Red	Yellow	Yellow
Compatibility	ACER ASUS HP LG	ACER	Gateway Hitachi Ienovo NEC SHARP Twinhead	ACER ASUS COMPAQ Fujitsu Gateway Hitachi HP IBM NEC Panasonic Philips Toshiba Winbook LG	ASUS	IBM Lenovo	НР	Samsung	Lenovo Yoga series

For Internal Use Only



How to select the adapter for my notebook?



(a) Check the label on the notebook bottom

or



(b) Check the label of your adapter

Voltage(V) x Current(A)= NB Wattage

Ex: $19V \times 2.37A = 45W$

 $19V \times 3.42A = 65W$

 $19V \times 4.74A = 90W$



Specifications



Product Name	NB Slim 90	NB Slim 120			
Output Watt	90W	120W			
Output Voltage	19V	19V			
Output Current	4.74A	6.32A			
Input Voltage	100-240Vac	100-240Vac			
Input Frequency	50-60Hz	50-60Hz			
Efficiency	More than 88%	More than 88%			
Standby power	≤0.1W	40 4141			
consumption	≥ 0.1 V V	≤0.1W			
No. of Tips	9				
Operating Temperature	0-40°C				
Protection	SCP / OCP / OVP / OTP				
Dimension	140 x 65.1 x 25.4mm	151.3 x 75.6 x 25.4mm			
Weight	233g	415g			



Package Information

Product Name	NB Slim 90	NB Slim 120	
Model Name	FSP090-ABCN2	FSP120-ABCN2	
EAN Code	471114048276 7	471114048275 0	
UPC Code	84568500351 5	84568500350 8	
Shipping Dimensions (L×W×H)	x x mm	x x mm	
Shipping Weight	g	g	
Unboxed Product Weight	g	g	
Master Pack Dimension (L×W×H)	x x mm	x x mm	
Master Pack Quantity	PCS	PCS	
Master Pack Weight	N/A	N/A	
Pallet Quantity (Per Layer)	N/A	N/A	
Country of Origin	China	China	
Warranty	3-Year	3-Year	
Additional Information			