



SPECIFICATIONS

| Model Name | A520M PRO |
|--------------------------|---|
| CPU Support | Support 3rd Gen AMD Ryzen [™] Desktop Processors and AMD |
| | Ryzen [®] 4000 G-Series Desktop Processors |
| CPU Socket | AMD Socket AM4 |
| Chipset | AMD A520 Chipset |
| Graphics | 1x PCI-E 3.0 x16 slot |
| Interface | |
| Display Interface | DisplayPort, HDMI, VGA - Requires Processor Graphics |
| Memory Support | 2 DIMMs, Dual Channel DDR4-4600MHz (OC) |
| Expansion Slots | 2x PCI-E 3.0 x1 slots |
| Storage | 1x M.2 Gen3 x4 slot, 4x SATA 6Gb/s ports |
| USB ports | 6x USB 3.2 Gen 1 5Gbps (Type-A) + 6x USB 2.0 |
| LAN | Realtek [®] RTL8111H Gigabit LAN |
| Audio | 8-Channel (7.1) HD Audio with Audio Boost |

FEATURES



Core Boost



With premium layout and fully digital power design to support more cores and provide better performance.

DDR4 Boost

Turbo M.2

Advanced technology to deliver pure data signals for the best gaming performance and stability.



Delivering Speeds Up to 32Gb/s



M.2 SHIELD FROZR

Onboard M.2 thermal solution to keep M.2 SSDs safe while preventing throttling, making them run cooler & faster.

Copper PCB 20z Thickened Copper PCB



AUDIC 80051 An enhanced PCB design improves heat dissipation and performance reliability.


EZ Debug LED

Easiest way to troubleshoot.

Audio Boost

Reward your ears with studio grade sound quality for the most immersive audio experience.

CONNECTIONS



1. VGA

- 3. LAN port
- 5. DisplayPort
- 7. USB 3.2 Gen 1 5Gbps Type-A
- 9. Audio Connectors
- 2. Keyboard / Mouse
- 4. HDMI
- 6. USB 2.0 Ports
- 8. USB 3.2 Gen 1 5Gbps Type-A

