

TSL-PS-S1M-01-W

## Smart power socket with power metering, white

### SMART HOME, SMART LIFE

- Quick and easy installation
- Works with free Tuya SmartLife app: your personal smart home control hub
- Easily turn your devices on and from anywhere in the world to give the impression that someone is home



### Vlastnosti

- Indoor single smart socket with power metering function
- Works via the Tuya smarthome platform easy smart control via the SmartLife app
- Universal: Can be embedded in any existing Tuya based smart home solution and combined with any other Tuya compatible products
- Voice Control: Works with Amazon Alexa and Google Assistant for voice control
- Schedule the Smart socket to automatically turn the connected device on or off
- Smart metering function provides clear insight in the power consumption of the connected device

### Packaging

Množství v kartonu, kusy	120
Velikost kartonu, CUM	0.0396
Váha kartonu, kg	12.95
Individual package size LxWxH:	55x55x85 mm
Carton size LxWxH:	450x320x275 mm
Země původu	CN
Čárkový kód (EAN)	8716309128391
Customs code	8538909910

### Obsah balení

Smart power socket  
User manual

### Specifikace

WiFi standard: 802.11 b/g/n  
Frequency range 2.4 GHz ~ 2.4835 GHz  
Max. transmit power: 17.68 dBm  
Input voltage: 220 240 VAC, 50 Hz  
Maximum AC load current: 16 A  
Maximum AC power load: 3680 W  
Fuse: 20 A  
Power meter: current 150 mA min step, voltage 3 V min step, power 0.5 W min step, energy (kWh) calculation  
Power meter tolerance: 5 %  
Stand-by power consumption: ? 0.5 W  
Dimensions: 52 mm x 52 mm x 82 mm  
Net weight: 84 g

### Systémové požadavky

2.4 GHz Wifi network  
TUYA App: Android or iOS smartphone

### Certifikát

